

Z-Wave Protocol Implementation Conformance Statement

FIBARO Smoke Sensor

General Information

Product Identifier:	FGSD-002
Brand Name:	FIBARO
Product Version:	2
Z-Wave Certification #:	ZC10-15070004

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1002
Z-Wave Product Type:	0x0C02
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max Nodes	Description
1 / 1	Z-Wave Plus Lifeline. Type of frame sent by the device when the association group is activated: DEVICE_RESET_LOCALLY_NOTIFICATION; NOTIFICATION_REPORT; BATTERY_REPORT; SENSOR_MULTILEVEL_REPORT.
2 / 5	Trigger: Smoke alarm - association group, value depends on the configuration. Type of frame sent by the device when the association group is activated: BASIC_SET.
3 / 5	Trigger: Tamper - association group. Type of frame sent by the device when the association group is activated: NOTIFICATION_REPORT.
4 / 5	Trigger: Smoke alarm ZW3 - association group for ZW3 backward compatibility. Type of frame sent by the device when the association group is activated: SENSOR_ALARM_REPORT.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

FIBARO Smoke Sensor

5 / 5 Trigger: Tamper ZW3 - association group for ZW3 backward compatibility. Type of frame sent by the device when the association group is activated: SENSOR_ALARM_REPORT.

Controlled Command Classes (2):

Basic

Time Parameters