

## Z-Wave Protocol Implementation Conformance Statement

### LED Bulb

#### General Information

<b>Product Identifier:</b>	ZW098-C55
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	62
<b>Z-Wave Certification #:</b>	ZC10-15070003

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0062
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
1 / 5	Group 1 is assigned to the Lifeline association group and every device has 5 nodes to associate. When the Bulb is turned on or off using the external switch, the Bulb will send a basic report of its status to the nodes in association group 1. To change what kind of signal is sent to the nodes in group 1, please see the detailed description of configuration parameter 80.
2 / 5	When the product receives a controlling Basic Set CC/Switch Binary Set CC/Switch Multilevel Start Level Change CC, Switch Multilevel Stop Level Change CC, Switch Multilevel Set CC, Scene Activation Set CC, which if cause the product's state to be changed, which will lead to send the Basic Set CC/Switch Binary Set

#### Controlled Command Classes (2):

Basic	Hail
-------	------