



## Z-Wave Protocol Implementation Conformance Statement

### Smart LED Light Bulb

#### General Information

**Product Identifier:** LBR30Z-1  
**Brand Name:** GoControl  
**Product Version:** HW: 255  
**Z-Wave Certification #:** ZC10-15070021

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? No  
SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x3038  
**Z-Wave Product Type:** 0x4754  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.51.06  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

Nodes

1 / 5	LBR30Z-1 supports Group 1 with up to 5 devices for lifeline communication. Group 1 must be assigned the Node ID of the controller to which unsolicited notifications will be sent. The Z-Wave controller should set this association automatically after inclusion. Lifeline association only supports the “manual reset” event. Please refer to the instructions manual of your remote controller or gateway for detail procedures on how these function can be set.
-------	---