

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Smart Switch Cover

#### General Information

<b>Product Identifier:</b>	WA00Z-1
<b>Brand Name:</b>	GoControl
<b>Product Version:</b>	HW: 255
<b>Z-Wave Certification #:</b>	ZC10-15100009

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3132
<b>Z-Wave Product Type:</b>	0x5343
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

#### Association Group Information

<b>Group # / Max Nodes</b>	<b>Description</b>
1 / 1	WA00Z-1 supports Group 1 for lifeline communication. Group 1 must be assigned the Node ID of the controller to which unsolicited notifications will be sent. The Z-Wave controller should set this association automatically after inclusion. Lifeline association only supports the "manual reset" event. Please refer to the instructions manual of your remote controller or gateway for detail procedures on how these function can be set.
2 / 5	WA00Z-1 supports Group 2 with up to five devices as association group. Press and Release the top/bottom button, the devices in Group 2 will be turned ON/OFF. Press and hold the top/bottom button, the devices in Group 2 will be dim up/down.
3 / 5	WA00Z-1 supports Group 3 with up to five devices as association group. Press and Release the top/bottom

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Smart Switch Cover

### Controlled Command Classes (1):

Basic