

Z-Wave Protocol Implementation Conformance Statement

Doorbell Gen5

General Information

| | |
|--------------------------------|-----------------|
| Product Identifier: | ZW056-C |
| Brand Name: | Aeotec |
| Product Version: | HW: 38 FW: 1.11 |
| Z-Wave Certification #: | ZC10-15110019 |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|-------------------------|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0038 |
| Z-Wave Product Type: | 0x0004 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.51.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Siren / Always On Slave |

Association Group Information

| Group # / Max Nodes | Description |
|---------------------|---|
| 1 / 5 | Association group 1 is the lifeline group. The Doorbell can add max 5 nodes to this group. The Basic report CC or Hail CC (can be configured by parameter 80) can be sent to the associated nodes in association group 1. |
| 2 / 5 | The Basic Set or Switch Binary Set can be sent to the associated nodes in this group when the Doorbell receives the Basic Set or Switch Binary Set CC from the primary controller. It can add max 5 nodes to this |

Controlled Command Classes (1):

Hail