

## Z-Wave Protocol Implementation Conformance Statement

### Door Sensor

#### General Information

<b>Product Identifier:</b>	NAS-DS01Z
<b>Brand Name:</b>	Coolcam
<b>Product Version:</b>	HW: 65 FW: 3.61
<b>Z-Wave Certification #:</b>	ZC10-16055076

#### Product Features

<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Battery Type</b>	CR2
<b>Color</b>	White
<b>Sensors</b>	Open/Closed (Binary)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1082
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Door Sensor

- 2 / 5            GROUP 2 allows for sending control commands to associated devices such as relay module, lighting, etc. This association group is configured through the advanced parameters no. 1 and 2. This Group Support: BASIC\_SET.
- 3 / 5            GROUP 3 allows for Send Notification to associated devices in this group. This Group Support: NOTIFICATION\_REPORT
- 4 / 5            GROUP 4 allows for Send Notification to associated devices in this group. This Group Support: SENSOR\_BINARY\_REPORT

#### Controlled Command Classes (1):

Basic