

## Z-Wave Protocol Implementation Conformance Statement

### Smart Power Plug

#### General Information

<b>Product Identifier:</b>	NAS-WR01Z
<b>Brand Name:</b>	Coolcam
<b>Product Version:</b>	HW: 65 FW: 3.70
<b>Z-Wave Certification #:</b>	ZC10-16055074

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Switch Load Capacity Volt-Ampere</b>	12A 220V
<b>Switch Type</b>	Push Button

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1087
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Power Plug

- 2 / 5            GROUP 2 allows for sending control commands to associated devices such as Siren, relay module, lighting, etc. If current load is over the max current defined in parameter #3, the Plug will send a BASIC\_SET (0xFF) to associated devices. When current load is normal, plug will send a BASIC\_SET (0x00) to associated devices.  
This Group Support: BASIC\_SET
- 3 / 5            GROUP 3 allows for Send Notification to associated devices in this group. This Group Support:  
NOTIFICATION\_REPORT\_V4

### Controlled Command Classes (1):

Basic