

## Z-Wave Protocol Implementation Conformance Statement

### Basic Remote Control Z-Wave

#### General Information

<b>Product Identifier:</b>	BRZ1
<b>Brand Name:</b>	Graber
<b>Product Version:</b>	HW: 255 FW: 187.65
<b>Z-Wave Certification #:</b>	ZC10-16055084

#### Product Features

<b>Switch Type</b>	Push Button with Indicator
<b>Window Covering Control Features</b>	Endpoint Aware
<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR2430 Lithium Coin
<b>Color</b>	White
<b>Firmware Updatable</b>	Not Updatable
<b>Switch Load Capacity Current</b>	.05
<b>Z-Wave Scene Type</b>	Central Scene
<b>Switch Load Capacity Watts</b>	.15

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Basic Remote Control Z-Wave

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x5A31
<b>Z-Wave Product Type:</b>	0x4252
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Portable Controller
<b>Z-Wave Device Type / Role Type:</b>	Remote Control - Simple / Portable Controller

### Association Group Information

**Group # / Max    Description**

**Nodes**

- |        |   |
|--------|---|
| 1 / 1  | Association Group #1 is dedicated Lifeline to primary control, primarily used for battery status reports, central scene cc, local reset cc. |
| 2 / 12 | Association Group #2 is dedicated for slave shades. Primary control commands, SWITCH_MULTILEVEL_CC,   |

**Controlled Command Classes (7):**

Association Group Information V1	Association V2
Basic V2	Central Scene V2
Switch Binary V2	Switch Multilevel V4
Wake Up V2	