

Z-Wave Protocol Implementation Conformance Statement

Dome Mouser

General Information

Product Identifier:	DMMZ1
Brand Name:	Dome
Product Version:	HW: 82 FW: 3.16
Z-Wave Certification #:	ZC10-16095211

Product Features

Battery Quantity	4
Battery Type	1.5V AA Size
Color	Dark Gray

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0086
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.06
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Dome Mouser

- 2 / 5 The Mouser sends a Basic Set command to Association Group 2 (or the Control Group) to directly trigger devices (like a light, chime, etc.) when it is tripped. After the trap is reset, a BASIC_SET(00) command is sent to reset the device (e.g. turn off the light.) The value of the Basic Set command (e.g. brightness of the lamp) is configured using configuration parameter 1.
- 3 / 5 Group 3 supports up to 5 members and the Mouser sends it a NOTIFICATION_REPORT when tripped, reset, armed, and disarmed.
- 4 / 5 Group 4 supports up to 5 members and the Mouser sends it a SENSOR_BINARY_REPORT when tripped, reset, armed, and disarmed.

Controlled Command Classes (1):

Basic