

## Z-Wave Protocol Implementation Conformance Statement

# Scene Controller

### General Information

<b>Product Identifier:</b>	HKZW-SCN01
<b>Brand Name:</b>	Hank
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-16085175

### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	LIR2450
<b>Z-Wave Scene Type</b>	Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0009
<b>Z-Wave Product Type:</b>	0x0200
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Scene Controller

- 2 / 5            Scene Controller will send Basic Set command to the associated nodes.
- 3 / 5            Scene Controller will send switch multilevel set, the multilevel start level change and multilevel stop level change command to the associated nodes.

### Controlled Command Classes (4):

Basic

Battery

Central Scene V2

Switch Multilevel V2