

Z-Wave Protocol Implementation Conformance Statement

FIBARO Button

General Information

Product Identifier:	FGPB-101
Brand Name:	FIBARO
Product Version:	HW: 1 FW: 3.02
Z-Wave Certification #:	ZC10-16105281

Product Features

Battery Quantity	1
Battery Type	ER14250 (1/2AA)
Firmware Updatable	Updatable by Consumer by RF
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x3000
Z-Wave Product Type:	0x0F01
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

FIBARO Button

- 2 / 5 On/Off is assigned to clicking the button and is used to turn on/off associated devices.
- 3 / 5 Dimmer is assigned to holding the button and is used to change level of associated devices.
- 4 / 5 Alarm is assigned to clicking and/or holding the button (triggers are defined in parameter 30) and is used to send alarm frames to associated devices.

Supported Command Classes (17):

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V5	Powerlevel
Security S0	Sensor Alarm
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Basic	Switch Multilevel V3
-------	----------------------