

## Z-Wave Protocol Implementation Conformance Statement

### Door/Window Sensor

#### General Information

<b>Product Identifier:</b>	HS-DS100+
<b>Brand Name:</b>	HomeSeer
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-17015379

#### Product Features

<b>Battery Quantity</b>	2
<b>Battery Type</b>	AAA
<b>Sensors</b>	Open/Closed (Binary)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0008
<b>Z-Wave Product Type:</b>	0x0201
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
Nodes	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door/Window Sensor

2 / 5            Sensor will send Basic Set to the associated nodes when the sensor body and magnet removed or combined.

### Supported Command Classes (13):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V5
Powerlevel	Security S0
Version V2	Wake Up V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Basic