

## Z-Wave Protocol Implementation Conformance Statement

### Siren Alarm

#### General Information

<b>Product Identifier:</b>	NAS-AB01Z
<b>Brand Name:</b>	Coolcam
<b>Product Version:</b>	HW: 48 FW: 2.90
<b>Z-Wave Certification #:</b>	ZC10-17025443

#### Product Features

<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Battery Quantity</b>	2
<b>Battery Type</b>	CR123A
<b>Color</b>	White
<b>Communications Connections</b>	RS-232 (Serial)
<b>Communications Protocol</b>	Z-Wave Serial API
<b>Z-Wave Scene Type</b>	Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Siren Alarm

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1088
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Siren / Listening Sleeping Slave

### Association Group Information

**Group # / Max**    **Description**

#### Nodes

1 / 5	GROUP 1 is lifeline service that assigned to Siren status. It enables the Siren to send reports and readings to Z Wave Controller or Z Wave Gateway whenever the sensor is triggered. This Group Support: SWITCH_BINARY_REPORT, NOTIFICATION_REPORT, BATTERY_REPORT, DEVICE_RESET_LOCALLY_NOTIFICATION
2 / 5	GROUP 2 allows for Send Binary Switch Report to associated devices in this group. This Group Support: SWITCH_BINARY_REPORT
3 / 5	GROUP 3 allows for Send Notification to associated devices in this group. This Group Support: NOTIFICATION_REPORT

#### Supported Command Classes (13):

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Indicator	Manufacturer Specific V2
Notification V8	Powerlevel
Switch Binary	Version V2
Z-Wave Plus Info V2	