

## Z-Wave Protocol Implementation Conformance Statement

### RS LED D2 Z-Wave

#### General Information

<b>Product Identifier:</b>	6772
<b>Brand Name:</b>	Steinel GmbH
<b>Product Version:</b>	HW: 1 FW: 1.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-17035489

#### Product Features

<b>Supported Notification Types</b>	Home Security System
<b>Switch Load Capacity Watts</b>	11
<b>Sensors</b>	Luminance Motion/No Motion (Binary)
<b>Switch Load Capacity Current</b>	0,070
<b>Switch Load Capacity Volt-Ampere</b>	17
<b>Z-Wave Scene Type</b>	Scene
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Outdoor Use</b>	No
<b>Neutral Wire Required</b>	No
<b>Electric Load Type</b>	LED
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## RS LED D2 Z-Wave

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1A74
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

#### Group # / Max Description

##### Nodes

1 / 1	Z-Wave Plus Lifeline - Device Reset Locally - Notifications: 0x09 (System) – Hardware failure with manufacturer proprietary code (0x03) 0x09 (System) – Software failure with manufacturer proprietary code (0x04) 0x07 (Home security) – Motion Begin event (0x08) 0x07 (Home security) – Motion End event (0x00, 0x08) - Binary Switch Report – lamp state - Multilevel Sensor Report – value of internal ambient light sensor
2 / 16	On/Off Control -Basic Set
3 / 16	Motion begin/end - Notifications: 0x07 (Home security) – Motion Begin event (0x08) 0x07 (Home security) – Motion End event (0x00, 0x08)
4 / 16	Ambient light - Multilevel Sensor Report – value of internal ambient light sensor

#### Supported Command Classes (20):

Application Status	Association Group Info
Association V2	Basic
Configuration	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific
Multi-Channel Association V3	Multi-Channel V4
Node Naming	Notification V4
Powerlevel	Scene Activation
Scene Actuator Conf	Sensor Multilevel V4
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

#### Controlled Command Classes (1):

Basic