

## Z-Wave Protocol Implementation Conformance Statement

### Mote

### General Information

<b>Product Identifier:</b>	FT130-B
<b>Brand Name:</b>	Oomi
<b>Product Version:</b>	HW: 130 FW: 1.07
<b>Z-Wave Certification #:</b>	ZC10-17045534

### Product Features

<b>Z-Wave Scene Type</b>	Central Scene
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Notification Types</b>	Power Management

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand
<b>Z-Wave Product ID:</b>	0x0082
<b>Z-Wave Product Type:</b>	0x0202
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.61.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Mote

- 2 / 5 When touching the Button 1, the Basic Set command will be sent to the associated nodes in Association group 2.
- 3 / 5 When touching the Button 1, the Multilevel Switch Set command will be sent to the associated nodes in Association group 3.
- 4 / 5 When touching the Button 2, the Basic Set command will be sent to the associated nodes in Association group 4.
- 5 / 5 When touching the Button 2, the Multilevel Switch Set command will be sent to the associated nodes in Association group 5.
- 6 / 5 When touching the Button 3, the Basic Set command will be sent to the associated nodes in Association group 6.
- 7 / 5 When touching the Button 3, the Multilevel Switch Set command will be sent to the associated nodes in Association group 7.
- 8 / 5 When touching the Button 4, the Basic Set command will be sent to the associated nodes in Association group 8.
- 9 / 5 When touching the Button 4, the Multilevel Switch Set command will be sent to the associated nodes in Association group 9.

### Supported Command Classes (16):

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V4	Powerlevel
Security S0	Version V2
Wake Up V2	Z-Wave Plus Info V2

### Controlled Command Classes (3):

Basic	Switch Binary V2
Switch Multilevel V4	