

Z-Wave Protocol Implementation Conformance Statement

Bellbox

General Information

Product Identifier:	BX-35ZW
Brand Name:	Climax Technology
Product Version:	HW: 255 FW: 1.04
Z-Wave Certification #:	ZC10-17055618

Product Features

Outdoor Use	Yes
Communications Protocol	Z-Wave Serial API
Battery Quantity	2
Battery Type	1.5V D Alkaline
Color	Red
Firmware Updatable	Updatable by Professional/Technician
Supported Notification Types	Home Security Power Management

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Bellbox

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0011
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.61.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Siren / Listening Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1	Group 1 for "LifeLine" (maximum node:1): Battery CC (COMMAND_CLASS_BATTERY) Notification CC,V4 (COMMAND_CLASS_NOTIFICATION) SwitchBinary CC, V1 (COMMAND_CLASS_SWITCH_BINARY) Device Reset Locally CC
2 / 5	Group 2 for "Tamp rep" (maximum node: 5): Notification CC,V4 (COMMAND_CLASS_NOTIFICATION) When Tamper Open, Group 2 send Notification (Type:07,Event:03), Tamper Close send Notification (Type:07,Event:00,Parameter:03)
3 / 5	Group 3 for "AC rep" (maximum node: 5): Notification CC,V4 (COMMAND_CLASS_NOTIFICATION) When AC Fail send Notification (Type:08,Event:02), When AC Restore send Notification (Type:08, Event:03)

Supported Command Classes (15):

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Notification V4	Powerlevel
Scene Activation	Security S0
Switch Binary	Version V2
Z-Wave Plus Info V2	