

## Z-Wave Protocol Implementation Conformance Statement

### LED Bulb

#### General Information

<b>Product Identifier:</b>	ZW098-D55
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 98 FW: 1.06
<b>Z-Wave Certification #:</b>	ZC10-17075675

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Type</b>	Toggle
<b>Z-Wave Scene Type</b>	Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Hong Kong
<b>Z-Wave Product ID:</b>	0x0062
<b>Z-Wave Product Type:</b>	0x0303
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### LED Bulb

2 / 5      In this group, the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands would be sent to the associated nodes in association group 2 when the Bulb receives the Basic Set, Switch Binary Set, Switch Multilevel Start Level Change, Switch Multilevel Stop Level Change, Switch Multilevel Set, Scene Activation Set commands from the main controller.

#### Supported Command Classes (15):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Switch Color
Switch Multilevel V2	Version V2
Z-Wave Plus Info V2	

#### Controlled Command Classes (2):

Basic	Hail
-------	------