

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall Touch Sensing Smart Dimmer

### General Information

<b>Product Identifier:</b>	14289/ZW3009
<b>Brand Name:</b>	GE
<b>Product Version:</b>	HW: 255 FW: 5.11
<b>Z-Wave Certification #:</b>	ZC10-17105823

### Product Features

<b>Switch Load Capacity Watts</b>	600W Incandescent, 150W Dimmable CFL/LED
<b>Neutral Wire Required</b>	Yes
<b>Electric Load Type</b>	Dimmable Fluorescent Dimmable LED
<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Color</b>	White

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3233
<b>Z-Wave Product Type:</b>	0x4944
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Touch Sensing Smart Dimmer

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                Z-Wave Plus Lifeline, Multi-level Switch Report, Device Reset Locally Notification.

2 / 5                Basic Set and is controlled with the local load.

**Supported Command Classes (15):**

Association Group Info	Association V2
Basic	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V2	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Switch All
Switch Multilevel V2	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic