

## Z-Wave Protocol Implementation Conformance Statement

### ON/OFF PLUG

#### General Information

<b>Product Identifier:</b>	AN186-1
<b>Brand Name:</b>	Everspring
<b>Product Version:</b>	HW: 1 FW: 1.00:00.05
<b>Z-Wave Certification #:</b>	ZC10-17115857

#### Product Features

<b>Color</b>	White
<b>Switch Load Capacity Watts</b>	1400
<b>Supported Notification Types</b>	Power Management
<b>Switch Load Capacity Current</b>	12
<b>Switch Load Capacity Volt-Ampere</b>	120
<b>Communications Connections</b>	None
<b>Electric Load Type</b>	Incandescent LED
<b>Sensors</b>	Power

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## ON/OFF PLUG

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x000C
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1	Association with 1 node.
2 / 4	Association with 4 nodes (i.e. end devices such as detectors or other lighting switches). This allows the On/Off module to receive commands directly from these end devices without the participation of the controller.

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific	Notification V4
Powerlevel	Security S0
Security S2	Supervision
Switch All	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic