

Z-Wave Protocol Implementation Conformance Statement

S100 iO Master Roller Blind

General Information

Product Identifier:	10002081-13X
Brand Name:	Simon
Product Version:	HW: 1 FW: 4.24:76.51
Z-Wave Certification #:	ZC10-18026014

Product Features

Neutral Wire Required	Yes
Z-Wave Scene Type	Central Scene
Firmware Updatable	Updatable by Professional/Technician

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0000
Z-Wave Product Type:	0x0005
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced Slave
Z-Wave Device Type / Role Type:	Wall Controller / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

S100 iO Master Roller Blind

2 / 20 ctrl. This group is used to add the devices to be controlled by Master Roller blind. Device sends Basic Sets, Multilevel Start or Stop level change when controlling sunblinds, and Manufacturer specific Gets, Configuration Gets and Sets when manual association is being performed over Simon devices.

Supported Command Classes (12):

Association Group Information V3

Basic

Configuration V2

Firmware Update Meta-Data V4

Powerlevel

Version V2

Association V2

Central Scene V3

Device Reset Locally

Manufacturer Specific V2

Switch Multilevel V3

Z-Wave Plus Info V2

Controlled Command Classes (5):

Association V2

Configuration V2

Switch Multilevel V3

Basic

Manufacturer Specific V2