

## Z-Wave Protocol Implementation Conformance Statement

### Smart Smoke Sensor

#### General Information

<b>Product Identifier:</b>	hm-hs1sa-z.eu
<b>Brand Name:</b>	Zipato
<b>Product Version:</b>	HW: 255 FW: 1.10
<b>Z-Wave Certification #:</b>	ZC10-17115870

#### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR123A
<b>Color</b>	White
<b>Supported Notification Types</b>	Smoke Alarm

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1000
<b>Z-Wave Product Type:</b>	0x8002
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Smoke Sensor

- 2 / 5 Association group 2: Root Device group(Binary Sensor) Binary Sensor Command Class: Compatible with 300 series 1-Binary Sensor reports status of smoke or no smoke via Lifeline. 2-When the sensor detects status change between smoke and no smoke, the device will be triggered.
- 3 / 5 Association group 3: Root Device group(Notification) 1-Notification reports reports status of detect smoke or no smoke via Lifeline. 2-When the sensor detects status change between smoke and no smoke, the device will be triggered.

### Supported Command Classes (11):

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific V2	Notification V4
Powerlevel	Sensor Binary V2
Version V2	Wake Up V2
Z-Wave Plus Info V2	