

## Z-Wave Protocol Implementation Conformance Statement

### B.One Smart Sensor

#### General Information

<b>Product Identifier:</b>	B1SS02-ZW-AU
<b>Brand Name:</b>	B.One
<b>Product Version:</b>	HW: 1 FW: 1.04
<b>Z-Wave Certification #:</b>	ZC10-18025994

#### Product Features

<b>Battery Quantity</b>	2
<b>Supported Notification Types</b>	Access Control Home Security
<b>Battery Type</b>	AAA
<b>Sensors</b>	Open/Closed (Binary)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Australia / New Zealand
<b>Z-Wave Product ID:</b>	0x0201
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.08
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## B.One Smart Sensor

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                Door/Window Sensor will send notification report and battery report to the associated nodes.

2 / 5                Sensor will send Basic Set to the associated nodes when the sensor body and magnet removed or combined.

**Supported Command Classes (13):**

- |                          |                              |
|--------------------------|------------------------------|
| Association Group Info   | Association V2               |
| Battery                  | Configuration                |
| Device Reset Locally     | Firmware Update Meta-Data V2 |
| Manufacturer Specific V2 | Notification V5              |
| Powerlevel               | Security S0                  |
| Version V2               | Wake Up V2                   |
| Z-Wave Plus Info V2      |                              |

**Controlled Command Classes (1):**

Basic