

## Z-Wave Protocol Implementation Conformance Statement

### Alert Button

#### General Information

<b>Product Identifier:</b>	T8343-JP
<b>Brand Name:</b>	Axis Communications
<b>Product Version:</b>	HW: 1 FW: 1.01:00.01
<b>Z-Wave Certification #:</b>	ZC10-18015971

#### Product Features

<b>Battery Quantity</b>	2
<b>Switch Type</b>	Push Button
<b>Battery Type</b>	AAA
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer via Internet
<b>Supported Notification Types</b>	Appliance

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0005
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Alert Button

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                Association with 1 node.

2 / 4                Association with 4 nodes (i.e. end devices such as smart plugs and other lighting controllers). This allows the On/Off module to receive commands directly from these end devices without the participation of the controller.

**Supported Command Classes (15):**

Association Group Info	Association V2
Battery	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Notification V4	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Wake Up V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic