

## Z-Wave Protocol Implementation Conformance Statement

### Door/Window Sensor

#### General Information

|                                |                      |
|--------------------------------|----------------------|
| <b>Product Identifier:</b>     | T8342-JP             |
| <b>Brand Name:</b>             | Axis Communications  |
| <b>Product Version:</b>        | HW: 1 FW: 1.01:00.01 |
| <b>Z-Wave Certification #:</b> | ZC10-18015967        |

#### Product Features

|                                     |                |
|-------------------------------------|----------------|
| <b>Supported Notification Types</b> | Access Control |
| <b>Battery Quantity</b>             | 2              |
| <b>Battery Type</b>                 | CR2450         |
| <b>Color</b>                        | White          |

#### Z-Wave Product Information

|                                      |   |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology?  | No  |
| Supports Z-Wave Network Security?    | Yes                                       |
| Supports Z-Wave AES-128 Security S0? | Yes                                       |
| Supports Security S2?                | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible?               | No  |

#### Z-Wave Technical Information

|  |  |
|--|--|
| <b>Z-Wave Frequency:</b>               | Japan  |
| <b>Z-Wave Product ID:</b>              | 0x0001   |
| <b>Z-Wave Product Type:</b>            | 0x0003   |
| <b>Z-Wave Hardware Platform:</b>       | SD3502   |
| <b>Z-Wave Development Kit Version:</b> | 6.71.01  |
| <b>Z-Wave Library Type:</b>            | Enhanced 232 Slave                             |
| <b>Z-Wave Device Type / Role Type:</b> | Notification Sensor / Reporting Sleeping Slave |

#### Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door/Window Sensor

2 / 4 Association with 4 nodes (i.e. end devices such as smart plugs and other lighting controllers). This allows the detector to transfer commands directly to end devices without the participation of the controller. This has the effect that when the detector triggers, all devices associated with detector will be operated.

### Supported Command Classes (15):

|                              |                          |
|------------------------------|--------------------------|
| Association Group Info       | Association V2           |
| Battery                      | Device Reset Locally     |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Notification V4              | Powerlevel               |
| Security S0                  | Security S2              |
| Supervision                  | Transport Service V2     |
| Version V2                   | Wake Up V2               |
| Z-Wave Plus Info V2          |                          |

### Controlled Command Classes (1):

Basic