



## Z-Wave Protocol Implementation Conformance Statement

### NanoMote One

#### General Information

**Product Identifier:** ZWA004-C  
**Brand Name:** Aeotec  
**Product Version:** HW: 1 FW: 1.00  
**Z-Wave Certification #:** ZC10-18036055

#### Product Features

**Battery Quantity** 1  
**Battery Type** LIR2450  
**Z-Wave Scene Type** Central Scene

#### Z-Wave Product Information

**Supports Z-Wave Beaming Technology?** No  
**Supports Z-Wave Network Security?** Yes  
**Supports Z-Wave AES-128 Security S0?** Yes  
**Supports Security S2?** Yes: S2 Unauthenticated  
**SmartStart Compatible?** No

#### Z-Wave Technical Information

**Z-Wave Frequency:** CEPT (Europe)  
**Z-Wave Product ID:** 0x0004  
**Z-Wave Product Type:** 0x0002  
**Z-Wave Hardware Platform:** ZM5101  
**Z-Wave Development Kit Version:** 6.71.01  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Wall Controller / Portable Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

NanoMote One

## Association Group Information

**Group # / Max**    **Description**

**Nodes**

- |       |   |
|-------|---|
| 1 / 5 | Scene Controller will send Scene Controller sends the central scene notification command and battery report command to the associated nodes.          |
| 2 / 5 | Scene Controller will send Basic Set command to the associated nodes.   |
| 3 / 5 | Scene Controller will send switch multilevel set, the multilevel start level change and multilevel stop level change command to the associated nodes. |

**Supported Command Classes (16):**

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific V2
Powerlevel	Security S0
Security S2	Supervision
Transport Service V2	Version V2
Wake Up V2	Z-Wave Plus Info V2

**Controlled Command Classes (3):**

Basic	Battery
Switch Multilevel V2	