

## Z-Wave Protocol Implementation Conformance Statement

### HC Dimmer FM

#### General Information

<b>Product Identifier:</b>	MT 02760
<b>Brand Name:</b>	devolo
<b>Product Version:</b>	HW: 4 FW: 3.08:03.10
<b>Z-Wave Certification #:</b>	ZC10-18025988

#### Product Features

<b>Color</b>	White
<b>Neutral Wire Required</b>	Yes
<b>Sensors</b>	Acceleration Y-Axis Air Temperature
<b>Supported Meter Type</b>	Electric Energy
<b>Supported Notification Types</b>	Power Management

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0051
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## HC Dimmer FM

### Association Group Information

#### Group # / Max Description

##### Nodes

1 / 5	Z-Wave Plus Lifeline
2 / 16	Basic on/off (triggered at change of the input I1 and reflecting state of the output Q)
3 / 16	Start level change/stop level change (triggered at change of the input I1 state and reflecting its state)
4 / 16	Multilevel set (triggered at changes of state/value of the Flush Dimmer) up to 16 nodes
5 / 16	Basic on/off (triggered at change of the input I2 state and reflecting its state) up to 16 nodes.
6 / 16	Notification report (triggered at change of the input I2 state and reflecting its state)
7 / 16	Binary sensor (triggered at change of the input I2 state and reflecting its state)
8 / 16	Basic on/off (triggered at change of the input I3 state and reflecting its state)
9 / 16	Notification report (triggered at change of the input I3 state and reflecting its state)
10 / 16	Binary sensor report (triggered at change of the input I3 state and reflecting its state)
11 / 16	Multilevel sensor report (triggered at change of temperature sensor)

#### Supported Command Classes (19):

Association Group Information V2	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Notification V5
Powerlevel	Security S0
Sensor Binary	Sensor Multilevel V7
Switch All	Switch Binary
Switch Multilevel V3	Version V2
Z-Wave Plus Info V2	

#### Controlled Command Classes (2):

Basic	Switch Multilevel V3
-------	----------------------