

## Z-Wave Protocol Implementation Conformance Statement

### LED Bulb 6: Multi-White

#### General Information

<b>Product Identifier:</b>	ZWA001-C
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.10
<b>Z-Wave Certification #:</b>	ZC10-18036060

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	
1 / 1	LED Bulb will send its status to the lifeline group when the state of the LED Bulb is changed. 1). Set Configuration parameter 0x50 to 0: nothing 2). Set Configuration parameter 0x50 to 1: Sending Basic Report

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## LED Bulb 6: Multi-White

### Supported Command Classes (18):

Association Group Info  
Basic  
Device Reset Locally  
Manufacturer Specific V2  
Scene Activation  
Security S0  
Supervision  
Switch Multilevel V2  
Version V2

Association V2  
Configuration  
Firmware Update Meta-Data V4  
Powerlevel  
Scene Actuator Conf  
Security S2  
Switch Color V2  
Transport Service V2  
Z-Wave Plus Info V2