

## Z-Wave Protocol Implementation Conformance Statement

### AMADAS Smart Door Lock

#### General Information

<b>Product Identifier:</b>	ADSL-1001
<b>Brand Name:</b>	AMADAS
<b>Product Version:</b>	HW: 1 FW: 1.18:01.02
<b>Z-Wave Certification #:</b>	ZC10-18026009

#### Product Features

<b>Color</b>	Silver
<b>Battery Type</b>	LR06 AA
<b>Sensors</b>	Heat Open/Closed (Binary)
<b>Door Lock Type</b>	Lever Handle
<b>Battery Quantity</b>	2
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Outdoor Use</b>	Yes
<b>Supported Notification Types</b>	Access Control Power Management

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## AMADAS Smart Door Lock

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	South Korea
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Door Lock - Keypad / Listening Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1            Supported Command Classes (13) : Z-Wave plus info (V2) - Manufacturer specific (V2) - Security (V1) - Device reset Locally (V1) - Battery (V1) - Power level (V1) - Version(V2) - Door Lock (V2) - User Code (V1) - Association (V2) - Association Group Info (V1) - Notification (V4) - Firmware update meta data (V2)

**Supported Command Classes (13):**

Association Group Info	Association V2
Battery	Device Reset Locally
Door Lock V2	Firmware Update Meta-Data V2
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
User Code	Version V2
Z-Wave Plus Info V2	