

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Plus Smart Switch - Double Toggle

### General Information

<b>Product Identifier:</b>	DTLS2-ZWAVE5
<b>Brand Name:</b>	Ecolink Intelligent Technology
<b>Product Version:</b>	HW: 255 FW: 10.01
<b>Z-Wave Certification #:</b>	ZC10-18026030

### Product Features

<b>Battery Quantity</b>	2
<b>Battery Type</b>	AA
<b>Color</b>	White
<b>Sensors</b>	Open/Closed (Binary)
<b>Switch Type</b>	Toggle

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0004
<b>Z-Wave Product Type:</b>	0x0006
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Listening Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Plus Smart Switch - Double Toggle

### Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 1            Group one is the lifeline group. The Light Switch will send Switch Binary Reports with a value of 0x00 if the light is turned off and 0xFF if the light is turned on to all nodes in group 2.
- 2 / 1            Group two – The light switch will send basic reports with a value of 0x00 if the light is turned off and 0xFF if the light is turned on to all nodes in group 2.

**Supported Command Classes (10):**

Association Group Info	Association V2
Basic	Battery
Device Reset Locally	Manufacturer Specific
Powerlevel	Switch Binary
Version V2	Z-Wave Plus Info V2