

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Wall Switch

#### General Information

<b>Product Identifier:</b>	HS-WS100+
<b>Brand Name:</b>	HomeSeer
<b>Product Version:</b>	HW: 255 FW: 50.03
<b>Z-Wave Certification #:</b>	ZC10-18036077

#### Product Features

<b>Electric Load Type</b>	ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	15 Amps
<b>Switch Load Capacity Watts</b>	900 Watts Incandescent
<b>Color</b>	White
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Scene & Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Wall Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3033
<b>Z-Wave Product Type:</b>	0x4447
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                Z-Wave Plus Lifeline

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Central Scene V3
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (2):**

Central Scene V3	Supervision
------------------	-------------