

Z-Wave Protocol Implementation Conformance Statement

In-wall Dimmer

General Information

Product Identifier:	SR-ZV9101SAC-HP-EU
Brand Name:	Sunricher
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-18046089

Product Features

Supported Notification Types	System
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0xD005
Z-Wave Product Type:	0x0200
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 5	1. When factory reset the dimmer, send "Device Reset Locally Notification CC" to associated devices of this group to report factory reset information. 2. When load state changes, send "Basic Report CC" to associated

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-wall Dimmer

Supported Command Classes (18):

Association Group Information V3

Basic V2

Device Reset Locally

Manufacturer Specific V2

Powerlevel

Scene Actuator Conf

Security S2

Switch Multilevel V4

Version V2

Association V2

Configuration V2

Firmware Update Meta-Data V4

Notification V8

Scene Activation

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2