



Z-Wave Protocol Implementation Conformance Statement

In-wall Dimmer

General Information

Product Identifier: SR-ZV9101SAC-HP-RU
Brand Name: Sunricher
Product Version: HW: 1 FW: 1.00
Z-Wave Certification #: ZC10-18056100

Product Features

Firmware Updatable Updatable by Consumer by RF
Supported Notification Types System

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Unauthenticated
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: Russia
Z-Wave Product ID: 0xD005
Z-Wave Product Type: 0x021A
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.71.01
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5
1. When factory reset the dimmer, send "Device Reset Locally Notification CC" to associated devices of this group to report factory reset information. 2. When load state changes, send "Basic Report CC" to associated

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-wall Dimmer

Supported Command Classes (18):

Command Class Association Group Info V3
Command Class Basic V2
Command Class Device Reset Locally
Command Class Manufacturer Specific V2
Command Class Powerlevel
Command Class Scene Actuator Conf
Command Class Security 2
Command Class Switch Multilevel V4
Command Class Version V2

Command Class Association V2
Command Class Configuration V2
Command Class Firmware Update Md V4
Command Class Notification V8
Command Class Scene Activation
Command Class Security
Command Class Supervision
Command Class Transport Service V2
Command Class Z-Wave+ Info V2