

Z-Wave Protocol Implementation Conformance Statement

Wall Controller

General Information

| | |
|--------------------------------|---------------------|
| Product Identifier: | SR-ZV9003T4-RGBW-RU |
| Brand Name: | Sunricher |
| Product Version: | HW: 1 FW: 1.10 |
| Z-Wave Certification #: | ZC10-18056117 |

Product Features

| | |
|---------------------------|-----------------------------|
| Firmware Updatable | Updatable by Consumer by RF |
| Z-Wave Scene Type | Central Scene |

Z-Wave Product Information

| | |
|--------------------------------------|-------------------------|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Unauthenticated |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|-----------------------------------|
| Z-Wave Frequency: | Russia |
| Z-Wave Product ID: | 0xa107 |
| Z-Wave Product Type: | 0x031A |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.71.01 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Wall Controller / Always On Slave |

Association Group Information

| Group # / Max | Description |
|---------------|--|
| Nodes | |
| 1 / 1 | 1. Send "Command Class Device Reset Locally" to associated devices of this group to report factory reset information when factory reset the wall controller. 2. Double click a group number of the wall controller to send |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Wall Controller

- 2 / 12 Press button "1" to activate group. 1.Press and hold down button "1" to switch the associated devices with a Basic Set commands. 2.Press PWM1-PWM4 buttons, direct control of associated devices using Color Switch Set commands. 3.Press and hold down PWM1-PWM4 buttons, direct control of associated devices using Color Switch Start Level Change commands. 4.Short touch or slide touch the "Color Wheel", direct control of associated devices using Color Switch Set commands. 5.Press and hold down brightness button, direct control of associated devices using Multilevel Switch Start Level Change commands. 6. Short press "play/pause" button,direct control of associated devices using Scene Activation Set, Scene ID = 255. 7. Press and hold down "play/pause" button, direct control of associated devices using Scene Conf Set, Scene ID = 255.
- 3 / 12 Press button "2" to activate group. 1.Press and hold down button "2" to switch the associated devices with a Basic Set commands. 2.Press PWM1-PWM4 buttons, direct control of associated devices using Color Switch Set commands. 3.Press and hold down PWM1-PWM4 buttons, direct control of associated devices using Color Switch Start Level Change commands. 4.Short touch or slide touch the "Color Wheel", direct control of associated devices using Color Switch Set commands. 5.Press and hold down brightness button, direct control of associated devices using Multilevel Switch Start Level Change commands. 6. Short press "play/pause" button,direct control of associated devices using Scene Activation Set, Scene ID = 255. 7. Press and hold down "play/pause" button, direct control of associated devices using Scene Conf Set, Scene ID = 255.
- 4 / 12 Press button "3" to activate group. 1.Press and hold down button "3" to switch the associated devices with a Basic Set commands. 2.Press PWM1-PWM4 buttons, direct control of associated devices using Color Switch Set commands. 3.Press and hold down PWM1-PWM4 buttons, direct control of associated devices using Color Switch Start Level Change commands. 4.Short touch or slide touch the "Color Wheel", direct control of associated devices using Color Switch Set commands. 5.Press and hold down brightness button, direct control of associated devices using Multilevel Switch Start Level Change commands. 6. Short press "play/pause" button,direct control of associated devices using Scene Activation Set, Scene ID = 255. 7. Press and hold down "play/pause" button, direct control of associated devices using Scene Conf Set, Scene ID = 255.

Supported Command Classes (14):

| | |
|------------------------------|--------------------------|
| Association Group Info | Association V2 |
| Central Scene V3 | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Powerlevel |
| Security S0 | Security S2 |
| Supervision | Transport Service V2 |
| Version V2 | Z-Wave Plus Info V2 |

Controlled Command Classes (5):

| | |
|----------------------|------------------|
| Basic V2 | Scene Activation |
| Scene Actuator Conf | Switch Color V3 |
| Switch Multilevel V4 | |