

Z-Wave Protocol Implementation Conformance Statement

Door/Window Sensor

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | 0000/9518 |
| Brand Name: | TechniSat |
| Product Version: | HW: 1 FW: 1.00 |
| Z-Wave Certification #: | ZC10-18066149 |

Product Features

| | |
|-------------------------------------|----------------------|
| Supported Notification Types | Home Security |
| Battery Type | AAA |
| Battery Quantity | 2 |
| Sensors | Open/Closed (Binary) |

Z-Wave Product Information

| | |
|--------------------------------------|-----|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | No |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0008 |
| Z-Wave Product Type: | 0x0200 |
| Z-Wave Hardware Platform: | ZM5202 |
| Z-Wave Development Kit Version: | 6.51.08 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Reporting Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Door/Window Sensor

2 / 5 Sensor will send Basic Set to the associated nodes when the sensor body and magnet removed or combined.

Supported Command Classes (13):

| | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Firmware Update Meta-Data V2 |
| Manufacturer Specific V2 | Notification V5 |
| Powerlevel | Security S0 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Basic