



## Z-Wave Protocol Implementation Conformance Statement

### Motion Switch LED

#### General Information

**Product Identifier:** 40111665101  
**Brand Name:** Steinel GmbH  
**Product Version:** HW: 1 FW: 1.132:02.35  
**Z-Wave Certification #:** ZC10-18076193

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Type</b>	Push Button
<b>Color</b>	White
<b>Supported Notification Types</b>	Emergency Alarm
<b>Sensors</b>	Luminance Motion/No Motion (Binary)
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Motion Switch LED

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x19FB
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Always On Slave

### Association Group Information

#### Group # / Max Description

##### Nodes

1 / 1	Z-Wave Plus Lifeline - Device Reset Locally - Notifications: 0x07 ( Home security ) – Motion Begin event ( 0x08 ) 0x07 ( Home security ) – Motion End event ( 0x00, 0x08 ) - Binary Switch Report – LED state - Multilevel Sensor Report – value of internal ambient light sensor - Central scene notification – button events
2 / 16	On/Off control -Basic Set
3 / 16	Movement detection - Notifications: 0x07 ( Home security ) – Motion Begin event ( 0x08 ) 0x07 ( Home security ) – Motion End event ( 0x00, 0x08 )
4 / 16	Ambient light - Multilevel Sensor Report – value of internal ambient light sensor
5 / 16	Button on/off -Basic Set
6 / 16	Button scene -Scene Activation Set
7 / 16	Button dim -Switch Multilevel Start Level Change -Switch Multilevel Stop Level Change

#### Supported Command Classes (21):

Application Status	Association Group Info
Association V2	Basic
Central Scene V3	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Notification V4
Powerlevel	Security S0
Security S2	Sensor Multilevel V4
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

#### Controlled Command Classes (3):

Basic	Scene Activation
Switch Multilevel V4	