

## Z-Wave Protocol Implementation Conformance Statement

### Paddle On/Off Switch

#### General Information

<b>Product Identifier:</b>	ZW303
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-18106283

#### Product Features

<b>Switch Load Capacity Volt-Ampere</b>	10A
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	1200W
<b>Switch Type</b>	Decorator Paddle Push with Indicator
<b>Color</b>	White
<b>Electric Load Type</b>	Fluorescent Incandescent LED

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Paddle On/Off Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xA001
<b>Z-Wave Product Type:</b>	0xA000
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1            Z-Wave Plus Lifeline

2 / 5            basic set command When the output of the ZW303 is changed, On (0xFF) or Off (0x00). The ZW303 will automatically send out a related basic set command. On (0xFF) or Off (0x00) to its associated group.

**Supported Command Classes (15):**

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S2
Supervision	Switch Binary
Transport Service V2	Version V3
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic V2