

## Z-Wave Protocol Implementation Conformance Statement

### Plug-In Module - ON/OFF

#### General Information

<b>Product Identifier:</b>	RF96APM
<b>Brand Name:</b>	Eaton
<b>Product Version:</b>	HW: 1 FW: 1.01:00.01
<b>Z-Wave Certification #:</b>	ZC10-18126336

#### Product Features

<b>Z-Wave Scene Type</b>	Central Scene
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	1400
<b>Loads Controlled</b>	2
<b>Supported Notification Types</b>	Appliance
<b>Electric Load Type</b>	ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Switch Load Capacity Current</b>	12 Amps

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-In Module - ON/OFF

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0050
<b>Z-Wave Product Type:</b>	0x0053
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 4            Z-Wave Plus Lifeline

2 / 4            Basic Set When the button on the unit is pressed, the unit will send a Basic Set command to the nodes of Group 2. When the unit is OFF, Basic Set Value = 0x00. When the unit is ON, Basic Set Value = 0xFF

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Security S2	Supervision
Switch All	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic