

## Z-Wave Protocol Implementation Conformance Statement

### S2 Double Plug with USB Port

#### General Information

<b>Product Identifier:</b>	ZEN25
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 255 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-18126338

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Notification Types</b>	Power Management
<b>Electric Load Type</b>	Incandescent LED
<b>Switch Load Capacity Current</b>	10 total between 2 outlets
<b>Loads Controlled</b>	2
<b>Supported Meter Type</b>	Electric Energy
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## S2 Double Plug with USB Port

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xA003
<b>Z-Wave Product Type:</b>	0xA000
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1	Z-Wave Plus Lifeline
2 / 5	on/off and overload notifications (BASIC_SET) to other devices in the group.

**Supported Command Classes (18):**

Association Group Info	Association V2
Basic V2	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V4
Multi-Channel Association V3	Multi-Channel V4
Notification V8	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2