

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Dim Remote Control

General Information

| | |
|--------------------------------|--------------------|
| Product Identifier: | SR-ZV9001K8-DIM-G4 |
| Brand Name: | Sunricher |
| Product Version: | HW: 1 FW: 1.26 |
| Z-Wave Certification #: | ZC10-19056465 |

Product Features

| | |
|---------------------------|-----------------------------|
| Z-Wave Scene Type | Central Scene |
| Firmware Updatable | Updatable by Consumer by RF |

Z-Wave Product Information

| | |
|--------------------------------------|-------------------------|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Unauthenticated |
| SmartStart Compatible? | No |

Z-Wave Technical Information

| | |
|--|----------------------------------|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0xa305 |
| Z-Wave Product Type: | 0x0300 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.71.03 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Wall Controller / Portable Slave |

Association Group Information

| Group # / Max | Description |
|---------------|--|
| Nodes | |
| 1 / 5 | 1. Send Command Class "Device Reset Locally Notification V1" to associated devices of this group to report factory reset information when factory reset the remote control. 2. When remote control battery power value |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Dim Remote Control

- 2 / 5 Short press I/O button of Group 2 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 2 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".
- 3 / 5 Short press I/O button of Group 3 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 3 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".
- 4 / 5 Short press I/O button of Group 4 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 4 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".
- 5 / 5 Short press I/O button of Group 5 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 5 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".

Supported Command Classes (17):

| | |
|------------------------------|--------------------------|
| Association Group Info | Association V2 |
| Battery | Central Scene V3 |
| Configuration | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Powerlevel |
| Security S0 | Security S2 |
| Supervision | Transport Service V2 |
| Version V2 | Wake Up V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (2):

| | |
|-------|----------------------|
| Basic | Switch Multilevel V4 |
|-------|----------------------|