

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Dim Remote Control

General Information

Product Identifier:	SR-ZV9001K8-DIM-G4
Brand Name:	Sunricher
Product Version:	HW: 1 FW: 1.26
Z-Wave Certification #:	ZC10-19056465

Product Features

Z-Wave Scene Type	Central Scene
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0xa305
Z-Wave Product Type:	0x0300
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	1. Send Command Class "Device Reset Locally Notification V1" to associated devices of this group to report factory reset information when factory reset the remote control. 2. When remote control battery power value

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Dim Remote Control

- 2 / 5 Short press I/O button of Group 2 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 2 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".
- 3 / 5 Short press I/O button of Group 3 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 3 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".
- 4 / 5 Short press I/O button of Group 4 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 4 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".
- 5 / 5 Short press I/O button of Group 5 to send ON/OFF command to associated devices of this group using Command Class "Basic Set V2". Press and hold down I/O button of Group 5 to send light intensity increase/decrease command to associated devices of this group using Command Class "Multilevel V4".

Supported Command Classes (17):

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Basic	Switch Multilevel V4
-------	----------------------