

## Z-Wave Protocol Implementation Conformance Statement

### In-Wall Smart Dimmer

#### General Information

|                                |                    |
|--------------------------------|--------------------|
| <b>Product Identifier:</b>     | 14321/46564/ZW3010 |
| <b>Brand Name:</b>             | Jasco              |
| <b>Product Version:</b>        | HW: 255 FW: 5.53   |
| <b>Z-Wave Certification #:</b> | ZC10-19056491      |

#### Product Features

|                              |                             |
|------------------------------|-----------------------------|
| <b>Firmware Updatable</b>    | Updatable by Consumer by RF |
| <b>Neutral Wire Required</b> | Yes                         |
| <b>Z-Wave Scene Type</b>     | Central Scene               |

#### Z-Wave Product Information

|                                      |   |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology?  | Yes                                       |
| Supports Z-Wave Network Security?    | Yes                                       |
| Supports Z-Wave AES-128 Security S0? | No  |
| Supports Security S2?                | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible?               | Yes                                       |

#### Z-Wave Technical Information

|  |                                       |
|--|---------------------------------------|
| <b>Z-Wave Frequency:</b>               | U.S. / Canada / Mexico                |
| <b>Z-Wave Product ID:</b>              | 0x3236                                |
| <b>Z-Wave Product Type:</b>            | 0x4944                                |
| <b>Z-Wave Hardware Platform:</b>       | ZM5202                                |
| <b>Z-Wave Development Kit Version:</b> | 6.81.03                               |
| <b>Z-Wave Library Type:</b>            | Enhanced 232 Slave                    |
| <b>Z-Wave Device Type / Role Type:</b> | Light Dimmer Switch / Always On Slave |

#### Association Group Information

| <b>Group # / Max</b> | <b>Description</b> |
|----------------------|--------------------|
| <b>Nodes</b>         |                    |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Smart Dimmer

- 2 / 5 Supports Basic Set and is controlled by pressing the ON or OFF button with the local load
- 3 / 5 Supports Basic Set and is controlled by double pressing the ON or OFF button

### Supported Command Classes (16):

|                          |                              |
|--------------------------|------------------------------|
| Application Status       | Association Group Info       |
| Association V2           | Basic V2                     |
| Central Scene V3         | Configuration V4             |
| Device Reset Locally     | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Powerlevel                   |
| Security S2              | Supervision                  |
| Switch Multilevel V4     | Transport Service V2         |
| Version V3               | Z-Wave Plus Info V2          |

### Controlled Command Classes (1):

Basic V2