

## Z-Wave Protocol Implementation Conformance Statement

### Dimmer Switch (Red Series)

#### General Information

<b>Product Identifier:</b>	LZW31-SN
<b>Brand Name:</b>	Inovelli
<b>Product Version:</b>	HW: 1 FW: 1.24:01.20
<b>Z-Wave Certification #:</b>	ZC10-19096762

#### Product Features

<b>Supported Meter Type</b>	Electric Energy
<b>Switch Load Capacity Watts</b>	600
<b>Z-Wave Scene Type</b>	Central Scene
<b>Firmware Updatable</b>	Updatable by Manufacturer

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Dimmer Switch (Red Series)

- 2 / 5 Basic Set
- 3 / 5 Switch Multilevel Set Group 3 can be used to keep the, "master" switch in sync with the "slave switches"
- 4 / 5 SWITCH\_MULTILEVEL\_START\_LEVEL\_CHANGE; SWITCH\_MULTILEVEL\_STOP\_LEVEL\_CHANGE  
Group 4 is so that an accessory switch can control multiple bulbs / dimmers with level change

#### Supported Command Classes (19):

- |                          |                              |
|--------------------------|------------------------------|
| Application Status       | Association Group Info       |
| Association V2           | Basic                        |
| Central Scene V3         | Configuration                |
| Device Reset Locally     | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Meter V3                     |
| Powerlevel               | Protection V2                |
| Security S0              | Security S2                  |
| Supervision              | Switch Multilevel V2         |
| Transport Service V2     | Version V2                   |
| Z-Wave Plus Info V2      |                              |

#### Controlled Command Classes (2):

- |       |                      |
|-------|----------------------|
| Basic | Switch Multilevel V2 |
|-------|----------------------|