

Z-Wave Protocol Implementation Conformance Statement

Button

General Information

Product Identifier:	FGPB-101
Brand Name:	FIBARO
Product Version:	HW: 1 FW: 3.02
Z-Wave Certification #:	ZC10-19076580

Product Features

Battery Type	ER14250 (½AA)
Battery Quantity	1
Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Home Security
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	South Korea
Z-Wave Product ID:	0xB000
Z-Wave Product Type:	0x0F01
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Button

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	Lifeline reports the device status and allows for assigning single device only (main controller by default).
2 / 5	On/Off is assigned to clicking the button and is used to turn on/off associated devices.
3 / 5	Dimmer is assigned to holding the button and is used to change level of associated devices.
4 / 5	Alarm is assigned to clicking and/or holding the button (triggers are defined in parameter 30) and is used to send alarm frames to associated devices.

Supported Command Classes (17):

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V5	Powerlevel
Security S0	Sensor Alarm
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (2):

Basic	Switch Multilevel V3
-------	----------------------