



## Z-Wave Protocol Implementation Conformance Statement

### KeyFob

#### General Information

**Product Identifier:** FGKF-601  
**Brand Name:** FIBARO  
**Product Version:** HW: 1 FW: 3.02  
**Z-Wave Certification #:** ZC10-19076602

#### Product Features

**Color** White  
**Firmware Updatable** Updatable by Consumer by RF  
**Z-Wave Scene Type** Central Scene  
**Battery Quantity** 1  
**Battery Type** CR2450

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? Yes  
Supports Security S2? No  
SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** Israel  
**Z-Wave Product ID:** 0x7000  
**Z-Wave Product Type:** 0x1001  
**Z-Wave Hardware Platform:** ZM5101  
**Z-Wave Development Kit Version:** 6.51.09  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Wall Controller / Portable Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## KeyFob

### Association Group Information

#### Group # / Max Description

##### Nodes

1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 5	“Square - On/Off” is assigned to clicking the button and is used to turn on/off associated devices.
3 / 5	“Square - Multilevel” is assigned to clicking and holding the button and is used to turn on/off and change level of associated devices.
4 / 5	“Circle - On/Off” is assigned to clicking the button and is used to turn on/off associated devices.
5 / 5	“Circle - Multilevel” is assigned to clicking and holding the button and is used to turn on/off and change level of associated devices.
6 / 5	“Cross - On/Off” is assigned to clicking the x button and is used to turn on/off associated devices.
7 / 5	“Cross - Multilevel” is assigned to clicking and holding the x button and is used to turn on/off and change level of associated devices.
8 / 5	“Triangle - On/Off” is assigned to clicking the button and is used to turn on/off associated devices.
9 / 5	“Triangle - Multilevel” is assigned to clicking and holding the button and is used to turn on/off and change level of associated devices.
10 / 5	“Minus - On/Off” is assigned to clicking the - button and is used to turn on/off associated devices.
11 / 5	“Minus - Multilevel” is assigned to clicking and holding the - button and is used to turn on/off and change level of associated devices.
12 / 5	“Plus - On/Off” is assigned to clicking the + button and is used to turn on/off associated devices.
13 / 5	“Plus - Multilevel” is assigned to clicking and holding the + button and is used to turn on/off and change level of associated devices.

#### Supported Command Classes (17):

Command Class Application Status	Command Class Association Group Info
Command Class Association V2	Command Class Battery
Command Class Central Scene V3	Command Class Configuration
Command Class CRC16 Encap	Command Class Device Reset Locally
Command Class Firmware Update Md V3	Command Class Manufacturer Specific V2
Command Class Multi Channel Association V3	Command Class Powerlevel
Command Class Protection V2	Command Class Security
Command Class Version V2	Command Class Wake Up V2
Command Class Z-Wave+ Info V2	

#### Controlled Command Classes (2):

Command Class Basic	Command Class Switch Multilevel V3
---------------------	------------------------------------