

## Z-Wave Protocol Implementation Conformance Statement

### KeyFob

#### General Information

<b>Product Identifier:</b>	FGKF-601
<b>Brand Name:</b>	FIBARO
<b>Product Version:</b>	HW: 1 FW: 3.02
<b>Z-Wave Certification #:</b>	ZC10-19076605

#### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR2450
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0xA000
<b>Z-Wave Product Type:</b>	0x1001
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## KeyFob

### Association Group Information

#### Group # / Max Description

##### Nodes

1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 5	“Square - On/Off” is assigned to clicking the button and is used to turn on/off associated devices.
3 / 5	“Square - Multilevel” is assigned to clicking and holding the button and is used to turn on/off and change level of associated devices.
4 / 5	“Circle - On/Off” is assigned to clicking the button and is used to turn on/off associated devices.
5 / 5	“Circle - Multilevel” is assigned to clicking and holding the button and is used to turn on/off and change level of associated devices.
6 / 5	“Cross - On/Off” is assigned to clicking the x button and is used to turn on/off associated devices.
7 / 5	“Cross - Multilevel” is assigned to clicking and holding the x button and is used to turn on/off and change level of associated devices.
8 / 5	“Triangle - On/Off” is assigned to clicking the button and is used to turn on/off associated devices.
9 / 5	“Triangle - Multilevel” is assigned to clicking and holding the button and is used to turn on/off and change level of associated devices.
10 / 5	“Minus - On/Off” is assigned to clicking the - button and is used to turn on/off associated devices.
11 / 5	“Minus - Multilevel” is assigned to clicking and holding the - button and is used to turn on/off and change level of associated devices.
12 / 5	“Plus - On/Off” is assigned to clicking the + button and is used to turn on/off associated devices.
13 / 5	“Plus - Multilevel” is assigned to clicking and holding the + button and is used to turn on/off and change level of associated devices.

#### Supported Command Classes (17):

Application Status	Association Group Info
Association V2	Battery
Central Scene V3	Configuration
CRC16 Encapsulation	Device Reset Locally
Firmware Update Meta-Data V3	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Protection V2	Security S0
Version V2	Wake Up V2
Z-Wave Plus Info V2	

#### Controlled Command Classes (2):

Basic	Switch Multilevel V3
-------	----------------------