

## Z-Wave Protocol Implementation Conformance Statement

### PIR-Z-Wave

#### General Information

<b>Product Identifier:</b>	IX32-Z-Wave
<b>Brand Name:</b>	KPL
<b>Product Version:</b>	HW: 255 FW: 5.36
<b>Z-Wave Certification #:</b>	ZC10-19076690

#### Product Features

<b>Sensors</b>	Motion/No Motion (Binary)
<b>Battery Type</b>	AA
<b>Supported Notification Types</b>	Home Security

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0003
<b>Z-Wave Product Type:</b>	0x0005
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## PIR-Z-Wave

2 / 2                    When the PIR sensor is triggered, it will send "BASIC SET" command to control these devices in Group2.

### Supported Command Classes (12):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Manufacturer Specific V2
Notification V4	Powerlevel
Sensor Binary V2	Version V2
Wake Up V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic