

## Z-Wave Protocol Implementation Conformance Statement

### Door/Window Sensor 7

#### General Information

<b>Product Identifier:</b>	ZWA008-A
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-19076677

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Sensors</b>	Open/Closed (Binary)
<b>Supported Notification Types</b>	Access Control Home Security Power Management
<b>Battery Quantity</b>	1
<b>Battery Type</b>	1/AA
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door/Window Sensor 7

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0007
<b>Z-Wave Product Type:</b>	0x0102
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5	Z-Wave Plus Lifeline
2 / 5	Control devices when magnet or external dry contacts trips
3 / 5	Sends our alarm message when magnet controlled or external dry sensor trips.
4 / 5	Sends alarm messages when tamper is tripped

**Supported Command Classes (18):**

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Sensor Binary V2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2