

## Z-Wave Protocol Implementation Conformance Statement

### S2 In-wall Smart Dimmer switch

#### General Information

<b>Product Identifier:</b>	ZW31
<b>Brand Name:</b>	EVA LOGIK
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-19086704

#### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable LED Incandescent
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	500W
<b>Switch Type</b>	Toggle
<b>Z-Wave Scene Type</b>	Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xAA02
<b>Z-Wave Product Type:</b>	0xA000
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.03

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## S2 In-wall Smart Dimmer switch

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                Z-Wave Plus Lifeline

2 / 5                basic set command

**Supported Command Classes (16):**

Association Group Info

Basic V2

Configuration

Firmware Update Meta-Data V4

Multi-Channel Association V3

Security S2

Switch Multilevel V4

Version V3

Association V2

Central Scene V3

Device Reset Locally

Manufacturer Specific V2

Powerlevel

Supervision

Transport Service V2

Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2