

## Z-Wave Protocol Implementation Conformance Statement

### Dual Relay In-Wall Module

#### General Information

<b>Product Identifier:</b>	AN196-0
<b>Brand Name:</b>	Everspring
<b>Product Version:</b>	HW: 1 FW: 1.01:00.01
<b>Z-Wave Certification #:</b>	ZC10-19096738

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x000E
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
1 / 5	When the unit is powered up for first time, a Notification Report will be sent to the node of Group 1. When performing Factory Reset, a Device Reset Locally Notification will be sent to the node of Group 1. When relay

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Dual Relay In-Wall Module

- 2 / 5            When switch 1 is pressed, a BASIC SET command containing a value will be sent to the node of Group 2  
(When relay is off, Basic Set Value=0x00, when relay is on, Basic Set Value=0xFF).
- 3 / 5            When switch 2 is pressed, a BASIC SET command containing a value will be sent to the node of Group 3  
(When relay is off, Basic Set Value=0x00, when relay is on, Basic Set Value=0xFF).

#### Supported Command Classes (18):

- |                          |                              |
|--------------------------|------------------------------|
| Association Group Info   | Association V2               |
| Basic                    | Configuration                |
| Device Reset Locally     | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Multi-Channel Association V3 |
| Multi-Channel V4         | Notification V8              |
| Powerlevel               | Security S0                  |
| Security S2              | Supervision                  |
| Switch Binary            | Transport Service V2         |
| Version V3               | Z-Wave Plus Info V2          |

#### Controlled Command Classes (1):

- Basic