

## Z-Wave Protocol Implementation Conformance Statement

### Single-Switch

#### General Information

<b>Product Identifier:</b>	0x00/9499
<b>Brand Name:</b>	TechniSat
<b>Product Version:</b>	HW: 6 FW: 2.00
<b>Z-Wave Certification #:</b>	ZC10-19126808

#### Product Features

<b>Neutral Wire Required</b>	Yes
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x1A90
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 1	The lifeline group reports the device's status.
2 / 10	Sends basic set commands according to the current state of the device to associated devices.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Single-Switch

### Supported Command Classes (18):

Association Group Info  
Basic V2  
Configuration  
Firmware Update Meta-Data V4  
Meter V4  
Powerlevel  
Security S2  
Switch Binary  
Version V3

Association V2  
Central Scene V3  
Device Reset Locally  
Manufacturer Specific V2  
Notification V8  
Security S0  
Supervision  
Transport Service V2  
Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic V2